



CARO commissioning AC011K-AE-35/ AC7000-AE-35





This document indicates how to commission the CARO charging station through APP EVCHARGO

APP EVCHARGO

 Download the Evchargo APP for smartphones own a charging station

E . When registering, check the second box if you



- From the first page after logging in, select charging **point** at the bottom and set it up.
- If you are configuring near the wallbox then you can select on **Nearby verification**, otherwise you can manually add or scan the QR code on the wallbox label.





11:33 🖪	֎ ∯ .ı 85% İ	10:11 🖪 🇭 🖲	হিন,না 65% 🖬	11:43 🖪	3	4 <u>9</u> + .⊪ 83% ∎
Autoconsumo	Pubblico	< Aggiungi un pu	nto di ricarica	<	Punti di ricarica vicir	ni
		Aggiungi un punto di Selezio ricarica marc	are il Configurare la comunicazione	Seleziona marchi	re il Aggiungi o un punto di l'operatore ricarica	Configurare la comunicazione
((- 1))				Selezio	nare il punto di ricarica	
					Aggiornamento	
		Svr121.666/1708-****			SN10052305255201	>
Collegare il punto di ric possibile controllare il	carica con l'APP, quindi è punto di ricarica tramite il					
telefono cellulare.		Scansionare il codice Q	R sul punto di ricarica			
		😑 Scansiona	re il codice QR			
	2	🕀 Aggiungi r	nanualmente			
+ Legare	e il punto di ricarica	Verifica nelle	e vicinanze			
الله Mappe Pur	ato di ricarica					
111	0 <	III C) <		III O	<





• Select ZCS brand



Select the communication mode:

- *Online:* The charger must be connected to the network via Wifi or Ethernet. In this way it is possible to monitor and give commands from the APP via smartphone remotely.
- *Bluetooth:* The charger communicates with your smartphone via Bluetooth. In this way, it is possible to monitor and give commands from the APP via smartphone only in the vicinity of the charger.
- *Plug in to charge:* Neither control nor monitor the charging session from your smartphone. Charging is only interrupted by the car.





If you choose the Online communication mode , proceed with the steps indicated below.

10:14 🖻 🏶 📵 🤤 👯 🔐 64% 🖬	10:14 🖻 🌪 📵 👘 🖓 📶 64% 🔳	10:14 🖻 🌪 (B) 🔅 🔅 10:64% 🖬
Selezionare la modalità di comunicazione	Configurare la rete	Configurare la rete
1 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2	Aggiungi Selezionare II Selezionare Configurare la un punto di marchio la modalità di reterità comunicazione	Aggiungi Selezionare il Selezionare Configurare la un punto di marchio la modalità di rete
Selezionare la modalità di comunicazione	Metodo di configurazione	Metodo di configurazione
(()) In linea	8 APP(Raccomandazione)	8 APP(Raccomandazione)
rete	Metodo di comunicazione	Metodo di comunicazione
Bluetooth	Seleziona il metodo di comunicazione $$	Seleziona il metodo di comunicazione
Il telefono e il punto di ricarica comunicano tramite bluetooth		🔶 WiFi
Si collegare per caricare		C Ethernet
Confermare	Saltare	Saltare
	III O <	

By selecting WiFi you will be asked to choose the network and enter the specific password. If the configuration is successful, you will have to display the wallbox on **Available** as in the screenshot below.







CONFIGURE RFID CARDS

To add RFID cards press on *Me, Card Management, Add a Card.* Once added, the identification code above will appear.



NETWORK CONFIGURATION VIA ACCESS POINT (AP)

In case you have network configuration problems via APP, you can also do it via access point (AP). Once the wallbox has been switched on, you have 10 **minutes** to log in via the access point, after which it must be switched off and on again.

The steps to follow:

- put your phone in airplane mode
- Turn on WiFi and search for the network with the same name as the SN serial code.....
- Log in and enter the password: admin123
- tick automatic reconnection
- type the address 192.168.4.1 on the search engine
- enter the 4-digit PIN that is present inside the box







By clicking on Network Setting I choose the connection mode:

- Wifi
- Ethernet

Once you have selected the connection mode, follow the network setup procedure. If you select Wifi you will be prompted to select the network and enter the network password. When you have completed the procedure, select *Confirm*.

10:05 @		জ+ 66%∎ 	10:05	10:05 P (A)			St 66%.	
A 192.1	68.4.1/#/funct	⊦	Δ (▲ 192.1	68.4.1/#/pileS	+ 💿		
	Home	English 🗸	<		Network Settings	English		
ateway S	N10052311306825-V	43.2.276		🔒 Ethe	ernet			
harger SN	SN1005231130682	5-1.4.859						
Communication Method Ethernet				33/9	://ocpp16.evchargo 5N10052311306825	.com:330		
erver Status	Disconnected							
letwork Stat	us Offline		1					
Network S	Erase data	er Settings			Confirm			
	Quit							